

X7 CW series programmable CCT adjustable intelligent driver



Features

- Input voltage: 90~305Vac;
- Isolated constant current design;
- current adjustable by software;
- Harmonics Current <10%;
- negative logic dimming 10-1V/5-1V/PWM optional, dual output, lightness and CCT adjust independently, RS485 optional;
- Surge protection: DM 6KV, CM10KV;
- Protection: OVP, OTP, input OVP;
- Dimming cable protection: reverse resistance 220~240Vac;
- IP67;
- Warranty 5 years

Application

- ▶ Tunnel lighting

Models

Model	Power(W)	Tunnel	Output voltage(Vdc)	Output current range(A)	Output current (A)	Typ. Eff	Typ. PF	Dimension (L*W*H)mm
X7-060M052CW	60	1	28~52	0.14~1.34	1.05	87.5%	0.95	145*68*35
		2	28~52	0.14~1.34	0.00			
X7-150M056CW	150	1	32~56	0.43~4.30	3.10	91.0%	0.96	190*68*37
		2	32~56	0.43~4.30	0.00			
X7-240M056CW	240	1	32~56	0.63~6.30	5.00	94.0%	0.95	226*68*37
		2	32~56	0.63~6.30	0.00			

Note:1. M means 0-10V;

2. suffix CW means CCT adjustable